

Simplified Fldigi / Flmsg installation:

Fldigi / Flmsg:

1. Download Fldigi from the link provided below.
2. Install the application and accept all the defaults.
3. Launch Fldigi and walk through the configuration wizard setting up your personal data, click "Next".
4. Select the "PortAudio" devices connected to your computer where capture device is your microphone and playback your speakers, click "Next", then don't make any other selection unless you have a dedicated cable for you radio then click "Finished".
5. Select "Configure", then "Misc".
6. Select "Sweet Spot", check "Always start new modems at these frequencies". CW, RTTY, PSK should all be at "1000" then click on "Save"
7. Select "Modems" on the top tab, Then select "MT-63", check 64-bit (long) interleave and 8-bit extended characters (UTF-8), then click on "Save".
8. Close the application then install Flmsg downloaded from the same location below. when installing accept all the defaults and just click "Next".
9. Launch Flmsg and fill out your personal data, and select "Close".
10. You can close Flmsg for now.
11. Launch Fldigi and select "Configure" in the upper tab then "Misc".
12. Select "NBEMS", check "Enable", "Open message folder", "Open with Flmsg", "Open in browser".
13. Click on Locate Flmsg and point to the Flmsg executable, "C:\ProgramFiles\fldigi-1.1.29\flmsg.exe", this will vary based on operating system and release. Click on "Save".
14. Download and install Flwrap. No further configuration is needed.

All required software is now configured and ready to use.

You can find the required software here <http://w1hkj.com/download.html>.